



Project/Job Name: _____

Location: _____

Fixture Type: _____

Notes: _____

S11954 - 5 Foot; 22 Watt; Linear LED T8; Type B Ballast Bypass;
G13 Bi-Pin Base; 80 CRI; 5000K



ELECTRICAL

Technology:	LED
Watts:	22W
Volts:	120V-277V
Lumens:	2800L
CRI:	80+
CCT (Kelvins):	5000K - Natural Light
Beam Spread :	160
Hours Rated:	50000
Dimmable:	Non-Dimmable -
Incandescent Equivalent :	40W
Fluorescent Equivalent :	58W
Operating Temperature :	-20C (-4F) to +45C (+113F)
Ballasting Requirements :	Ballast Bypass
Lamp Ballast Type A/B/C :	Type B
Lamp End Type :	Single Ended
THD:	25%
Power Factor :	0.9
Light Source:	LED
Voltage Type:	AC Only; Range Voltage
Warranty:	5-Years

PACKAGING

Each UPC:	045923119545
Each Quantity:	1
Each Dimensions:	61.40 x 1.10 x 1.10

INFO

Installation Note:	Not for use in vapor tight fixtures.
Shatterproof Type:	PET Coated
Tube Guard Use:	Yes

PHYSICAL

Base:	Medium Bi Pin
Shape:	T8
Finish:	Frost
Lens Finish:	Frost
Lens Material:	Glass
Dimensions (In.):	MOL: 60 - MOD: 1
Nominal Length:	60
Weight (Lbs.):	0.77
Material:	Glass
Housing Color:	White

COMPLIANCE

Safety Listing:	cULus - Classified; cULus - Certified; cRUus - Recognized Component; ETLus - Sanitation Recognized Component
Location Rating:	Damp
Indoor/Outdoor:	Indoor
DLC Approved:	No
BAA Compliant:	No
NOM Certificate No.:	NTE21CJTEN000079
Rated For Enclosed Fixture:	Yes
FCC Compliant:	Yes
IP Rating:	IP20
NSF Approved:	Yes
RoHS Compliant:	Yes
Restrictions:	No Restrictions

ACCESSORIES



80-2626 1-Light ballast bypass wiring harness for linear LED T8 lamps



80-2627 2-Light ballast bypass wiring harness for linear LED T8 lamps



80-2628 3-Light ballast bypass wiring harness for linear LED T8 lamps



80-2629 4-Light ballast bypass wiring harness for linear LED T8 lamps



S8000 5 Watt LED Emergency Driver; 120-277 Volts



S8002 10 Watt LED Emergency Driver; 120-277 Volt
