



Project/Job Name:

Location:

Fixture Type:

Notes:

**S11955** - 30 Watt T8 LED; Type B Ballast Bypass; G13 Bi-Pin Base; 80 CRI; 4000K; Single Ended



#### ELECTRICAL

Technology:	LED
Watts:	30W
Volts:	120V-277V
Lumens:	4000L
CRI:	80+
CCT (Kelvins):	4000K - Cool White
Beam Spread :	160
Hours Rated:	50000
Dimmable:	Non-Dimmable -
Incandescent Equivalent :	125W
Fluorescent Equivalent :	70W
Operating Temperature :	-20C (-4F) to +45C (+113F)
Ballasting Requirements :	Ballast Bypass
Lamp Ballast Type A/B/C :	Type B
Lamp End Type :	Single Ended
THD:	25%
Power Factor :	0.9
Light Source:	LED
Voltage Type:	AC Only; Range Voltage
Warranty:	5-Years

#### PACKAGING

Each UPC:	045923119552
Each Quantity:	1
Each Dimensions:	71.90 x 1.10 x 1.10

#### PHYSICAL

Base:	Medium Bi Pin
Shape:	T8
Finish:	Frost
Lens Finish:	Frost
Lens Material:	Glass
Dimensions (In.):	MOL: 70 - MOD: 1
Nominal Length:	70
Weight (Lbs.):	0.84
Material:	Glass
Housing Color:	White

#### COMPLIANCE

Safety Listing:	cULus - Classified; cULus - Certified; cRUs - Recognized Component; ETLus - Sanitation Recognized Component
Location Rating:	Damp
Indoor/Outoor:	Indoor
DLC Approved:	No
BAA Compliant:	No
NOM Certificate No.:	NTE21CJTENo000079
Rated For Enclosed Fixture:	Yes
FCC Compliant:	Yes
IP Rating:	IP20
NSF Approved:	Yes
RoHS Compliant:	Yes
Restrictions:	No Restrictions

#### INFO

Installation Note:	Not for use in vapor tight fixtures.
Shatterproof Type:	PET Coated
Tube Guard Use:	Yes



**S11955** - 30 Watt T8 LED; Type B Ballast Bypass; G13 Bi-Pin Base;  
80 CRI; 4000K; Single Ended

## ACCESSORIES



**80-2626** 1-Light ballast bypass wiring harness for linear LED T8 lamps



**80-2627** 2-Light ballast bypass wiring harness for linear LED T8 lamps



**80-2628** 3-Light ballast bypass wiring harness for linear LED T8 lamps



**80-2629** 4-Light ballast bypass wiring harness for linear LED T8 lamps



**S8000** 5 Watt LED Emergency Driver; 120-277 Volts



**S8002** 10 Watt LED Emergency Driver; 120-277 Volt