



Project/Job Name: _____

Location: _____

Fixture Type: _____

Notes: _____

S9950 - 23 Watt PLL LED ballast bypass; 2G11 base; 2800 Lumens; 120-277 Volt; 3500K; Type B; Ballast Bypass



ELECTRICAL

Technology:	LED
Watts:	23W
Volts:	120V-277V
Lumens:	2800L
CRI:	80+
CCT (Kelvins):	3500K - Neutral White
Beam Spread :	270
Hours Rated:	50000
Fluorescent Equivalent :	40W
Operating Temperature :	-20C (-4F) to +45C (+113F)
Ballasting Requirements :	Ballast Bypass
Lamp Ballast Type A/B/C :	Type B
Operating Position:	Universal
THD:	20%
Power Factor :	0.9
Light Source:	LED
Voltage Type:	Range Voltage
Warranty:	5-Years

PACKAGING

Each UPC:	045923099502
Each Quantity:	1
Each Dimensions:	23.00 x 1.80 x 1.10

INFO

Additional Info:	CCT Selectable Option: S18423
Installation Note:	Not for use in vapor tight fixtures.
ROI Category:	Internal-driver/Line Voltage (UL Type B) Lamps

PHYSICAL

Base:	4-Pin
Shape:	T5
Finish:	Frost
Dimensions (In.):	MOL: 22.5 - MOD: 0.63
Weight (Lbs.):	0.38
Material:	Aluminum / Plastic
Housing Color:	White

COMPLIANCE


Safety Listing:	cULus - Classified; cULus - Certified
Location Rating:	Damp
DLC Approved:	Yes
DLC Classification:	Standard
DLC ID:	PoO7T912
BAA Compliant:	No
NOM Certificate No.:	NTEEL21006443-SOLINTEEL21006443-SOL-FR1
NOM Expiration Date:	12/4/2021
Enclosure Rating:	Enclosed Rated Lamp
Rated For Enclosed Fixture:	Yes
FCC Compliant:	Yes
NSF Approved:	Yes
RoHS Compliant:	Yes
Restrictions:	No Restrictions



S9950 - 23 Watt PLL LED ballast bypass; 2G11 base; 2800 Lumens;
120-277 Volt; 3500K; Type B; Ballast Bypass

ACCESSORIES

	S8000	5 Watt LED Emergency Driver; 120-277 Volts
----------------------------------------------------------------------------------	--------------	--------------------------------------------

	S8002	10 Watt LED Emergency Driver; 120-277 Volt
----------------------------------------------------------------------------------	--------------	--------------------------------------------
