Ceiling Pendant

START FROM HERE

- $\ensuremath{\cdot}$ Make sure $\ensuremath{\mathsf{POWER}}$ is $\ensuremath{\mathsf{COMPLETELY}}$ OFF at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- Wear gloves at all time during this installation
- Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Technical Support: 1-855-855-8926

- 1. Remove fixture from its original package
- 2. Separate mounting plate (1c) from canopy (2a) by removing decorative nuts (2c)
- **3.** Align mounting plate screws (1d) to desired orientation, and then attach mounting plate (1c) to electrical junction box (1a) using screws provided (1e) in hardware package
- To change fixture height, push and hold wire gripper (2g), slide wire to desired length and then release wire gripper (2g) to secure (Remove excess wire if necessary)
- Make proper electrical connections (black to hot "L", white to neutral "N", ground to "GND") with wire nuts (1b) provided in hardware package
- **6.** Align and insert mounting plate screws (1d) through holes on canopy (2a), secure with decorative nuts (2c)
- Insert lamp (3g) into socket inside fixture body (3a), secure with lamp holder (3h), and then slide decorative glass (3b) into place
- **8.** Fine tone wire length if necessary, by push and hold wire gripper (2g) and then adjust wire to desired length

Please Note:

- This Kuzco LED fixtures come with pre-wired LED module(s)
- ${\boldsymbol{\cdot}}$ Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary
- contact with the module could cause permanent damage • Use TRIAC type of dimmer for dimming application

1a.

1b.-1c.-1d._ 1e. 2a. 2c. 2g. 3b. 3a. 3g. 3h.

19054 28th Avenue Surrey, BC Canada V3Z 6M3 T: 604 538 7162 TF: 1-855 85 KUZCO F: 604 538 7196 W: kuzcolighting.com 20190628