

Project:

Fixture Type: Location:

Contact:

Images:

One-Light Outdoor

Ceiling flush mounted • Damp location listed PROGRESS LED

Description:

6" flush mount cylinder. The P5741 Series are ideal for a wide variety of interior and exterior applications including residential and commercial. The Cylinders feature a 120V alternating current source and eliminates the need for a traditional LED driver. This modular approach results in an encapsulated luminaire that unites performance, cost and safety benefits.

Specifications:

- Metallic Gray (-82) (powder coat paint) •
- Die cast and extruded aluminum Construction .
- · Ideal for a wide variety of interior and exterior applications.
- Die-cast aluminum construction with durable powder coated finish •
- 1,050 lumens 29 lumens/watt (delivered) •
- 3000K color temperature, 90+ CRI
- Dimmable to 10% brightness (See Dimming Notes)
- · Unit covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included •
- 6" of wire supplied •
- · Meets California Title 24 high efficacy requirements for outdoor use only

Performance:

Number of Modules	1	
Input Power	29.4w	
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Delivered)	1,050/29 (LM-79)	
CCT	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	
FCC	FCC Title 47, Part 15, Class B	
Min. Start Temp	-30 °C	
Max. Operating Temp	30 ℃	
Warranty	5 year warranty	
Labels	cCSAus Damp location listed	
	Meets California Title 24 high efficacy requirements	
	for outdoor use only	

P5741-82/30K



Dimensions:

Diameter: 6" Height: 12"



One-Light Outdoor

Ceiling flush mounted • Damp location listed PROGRESS LED

P5741-82/30K

Dimming Notes:

P5741 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P Lutron Nova NTELV-300 Lutron Vierti VTELV-600 Lutron MAELV-600 Lutron SPELV-600 Leviton AWRMG-EAW Leviton 6615-P

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.