

## Low Voltage Track Cylinder

Model No. TL7301-ORB

Project Details	
Job Name	<input type="text"/>
Location	<input type="text"/>
Type/Qty	<input type="text"/>
Contact Info	<input type="text"/>
Note	<input type="text"/>

## Features

- Directional light source providing 140° vertical aiming capability with 310° horizontal rotation
- Head length: 4", Dia.:2.5"
- Dimmer compatible
- Suction cup lamp removal aid included
- Ceramic 12V AC MR16 base socket
- May be modified to fit other major brands
- I/P: AC 120V 60Hz 0.6A
- O/P: AC 12V 80W max. \*
- \* Our 80 watt rating is reserved for Trac-Tech low voltage cylinders built to the highest standards. Although rated for use with 50 watt bulbs, these heads feature top quality 80 watt electronic transformers to allow a longer, trouble-free life.

SPECIFICATION	
OAH (in.)	6
Overall Width (in.)	2.5
OA Depth (in.)	4
Bulb	MR16CG 12V
Max. wattage (W)	50
Number of Bulbs	1
Bulb included	No
Dimmable	Yes
Voltage	12V
Certifications and Listings	ETL Listed
Warranty	1 Year

### LED Info



## Description

Low voltage track head cylinder in a Oil Rubbed Bronze finish for use with MR16CG 12V/50W Lamps

LINE DRAWING  
CURRENTLY UNAVAILABLE



IMAGE COMING SOON



KENDAL Lighting (BC) Inc.

#110, 6780 Dennett Place Delta, B.C. V4G 1N4 Ph: (604) 952-5510 · Toll Free: 1-888-306-3267

info@kendallighting.com www.kendallighting.com